

Document Type:	Tech Brief
Document ID:	TB006_MR
Last Modified Date:	6/1/2017 2:42 PM

Challenge:

Going online and Downloading to a GE QuickPanel Plus

Solution: The Panel will open the W7E environment. Press “Start”, “Settings” and “Network and Dial Up Connections”. Select the LAN port you are connected to and open the dialog. Select Specify an IP Address. Touch the first Byte of the address and a Keyboard will pop up. Enter the IP Address and Submask. Click OK.

BE SURE YOU PC IS ON THE SAME SUBNET AS THE QP+

Open the Machine Edition with the same QP+ as you have connected. Right Click on the Target you are going online with, select Properties. Scroll down the Properties until you see Computer Address. Enter the IP address that was just set in the QP+. Right Click on the Target and select “Download and Start”. A Window will pop up indicating “Connecting” The following will appear in the Feedback Zone:

If you fail to connect, be sure you can ping the Computer Address from you PC. If you connect the Feedback zone displays the progress of the download. If there are any problems the download will stop indicating the error. Shift F3 will cycle through the errors. If you click on the error the Companion will display an explanation of the error and possible remedies. After all the errors are corrected the program will download and the QP+ will restart. It should open the main screen of the program.

Original Author: Marty Rubenstein on 5/26/2017
Key Words: #QP #QP+ #quickpanel #QuickPanel #quickpanelplus #QuickPanelPlus #QuickPanel+ #quickpanel+ #GEHardware #HMI #quick #panel #plus
Products: GE QuickPanel Plus
Version History: Original version